SCOPE OF CLAIMS

1. A wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, with a receiving apparatus having N (N is an integer of 2 or greater), said receiving apparatus comprising:

5   means for performing nulling representative of orthogonalization of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission antennas; and

means for demodulating said transmitted signals based on the

10   nulled signals.

2. A wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, with a receiving apparatus having N (N is an integer of 2 or greater), said receiving apparatus comprising:

5   means for performing nulling representative of orthogonalization of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission antennas; and

means for calculating and outputting a likelihood for said

10   transmitted signals based on the nulled signals.

3. A wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, with a receiving apparatus having N

(N is an integer of 2 or greater), said receiving apparatus comprising:

5   means for performing nulling representative of orthogonalization of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission antennas; and

means for outputting a likelihood for bits of said transmitted

10   signals based on the nulled signals.

4.   A wireless communication system according to any one of claims 1 through 3, wherein said means for performing nulling uses a complex conjugate transposed matrix of a Q matrix produced by QR-decomposing the channel matrix as nulling.

5

5.   A wireless communication system according to any one of claims 1 through 3, wherein said transmitted signals are demodulated in a descending order from a transmitted sequence transmitted from an Mth transmitted antenna to a transmitted sequence transmitted from a first

5   transmitted antenna, based on the nulled signals.

6.   A wireless communication system according to any one of claims 1 through 5, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the channel matrix of said channel coefficients and outputting a Q matrix and an

R matrix;

a Q^H processor for multiplying a received signal vector having

10   said received signals as elements by a complex conjugate transposed matrix

of said Q matrix and outputting the product as a converted signal; and

a transmitted sequence estimator for outputting at least one of a

transmitted sequence, a likelihood for said transmitted sequence, and a

likelihood for bits transmitted by said transmitted sequence, based on said

15   converted signal and said R matrix.

7.   A wireless communication system according to any one of claims

1 through 5, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said

channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the

channel matrix of said channel coefficients and outputting a Q matrix and an

R matrix;

a Q^H processor for multiplying a received signal vector having

10   said received signals as elements by a complex conjugate transposed matrix

of said Q matrix and outputting the product as a converted signal;

a transmitted symbol candidate selector for selecting and

outputting a symbol candidate for said converted signal based on said

received signals; and

15   a transmitted sequence estimator for outputting at least one of a

transmitted sequence, a likelihood for said transmitted sequence, and a

likelihood for bits transmitted by said transmitted sequence, based on said

converted signal, said symbol candidate, and said R matrix.

8.   A wireless communication system according to any one of claims 1 through 5, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the

10   channel coefficients estimated by said channel coefficient estimator and the priorities determined by said priority determiner, and outputting a modified channel matrix;

a QR decomposer for performing QR decomposition on said modified channel matrix and outputting a Q matrix and an R matrix;

15   a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a

20   likelihood for bits transmitted by said transmitted sequence, based on said converted signal and said R matrix; and

a restorer for restoring and outputting at least one of said transmitted sequence, the likelihood for said transmitted sequence, and the likelihood for bits transmitted by said transmitted sequence, based on the

25 output from said transmitted sequence estimator and said priorities.

9. A wireless communication system according to any one of claims 1 through 5, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the channel matrix of said channel coefficients and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having

10 said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted signals based on said received signals and outputting the determined

15 candidate sequences as transmitted sequence candidates; and

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, and said transmitted sequence candidates.

20

10. A wireless communication system according to any one of claims 1 through 5, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a priority determiner for determining priorities between

transmission sequences transmitted from said transmission antennas based

on said received signals;

a sorter for sorting said channel coefficients based on the

10   channel coefficients estimated by said channel coefficient estimator and the

priorities determined by said priority determiner, and outputting a modified

channel matrix;

a QR decomposer for performing QR decomposition on said

modified channel matrix and outputting a Q matrix and an R matrix;

15   a Q^H processor for multiplying a received signal vector having

said received signals as elements by a complex conjugate transposed matrix

of said Q matrix and outputting the product as a converted signal;

a transmitted symbol candidate selector for selecting a symbol

candidate for a demodulated sequence based on said received signals, and

20   outputting a transmitted symbol candidate;

a transmitted sequence estimator for outputting at least one of a

transmitted sequence, a likelihood for said transmitted sequence, and a

likelihood for bits transmitted by said transmitted sequence, based on said

converted signal, said R matrix, and said transmitted symbol candidate; and

25   a restorer for restoring and outputting at least one of said

transmitted sequence, the likelihood for said transmitted sequence, and the

likelihood for bits transmitted by said transmitted sequence, based on the

output from said transmitted sequence estimator and said priorities.

11.   A wireless communication system according to any one of claims

83

1 through 5, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5 transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the

10 channel coefficients estimated by said channel coefficient estimator and the priorities determined by said priority determiner, and outputting a modified channel matrix;

a QR decomposer for performing QR decomposition on said modified channel matrix and outputting a Q matrix and an R matrix;

15 a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted

20 signals based on said received signals and outputting the determined candidate sequences as transmitted sequence candidates;

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said

25 converted signal, said R matrix, and said transmitted sequence candidates; and

a restorer for restoring and outputting at least one of said

transmitted sequence, the likelihood for said transmitted sequence, and the

likelihood for bits transmitted by said transmitted sequence, based on the

30   output from said transmitted sequence estimator and said priorities.

12.   A wireless communication system according to any one of claims

1 through 5, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said

channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the

channel matrix of said channel coefficients and outputting a Q matrix and an

R matrix;

a Q^H processor for multiplying a received signal vector having

10   said received signals as elements by a complex conjugate transposed matrix

of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining

candidate sequences for L (L is an integer ranging from 1 to M) converted

signals based on said received signals and outputting the determined

15   candidate sequences as transmitted sequence candidates;

a transmitted symbol candidate selector for selecting and

outputting symbol candidates for (M-L) demodulated signals based on said

received signals; and

a transmitted sequence estimator for outputting at least one of a

20   transmitted sequence, a likelihood for said transmitted sequence, and a

likelihood for bits transmitted by said transmitted sequence, based on said

converted signal, said R matrix, said transmitted sequence candidates, and

said symbol candidates.

13. A wireless communication system according to any one of claims 1 through 5, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5 transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the

10 channel coefficients estimated by said channel coefficient estimator and the priorities determined by said priority determiner, and outputting a modified channel matrix;

a QR decomposer for performing QR decomposition on said modified channel matrix and outputting a Q matrix and an R matrix;

15 a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted

20 signals based on said received signals and outputting the determined candidate sequences as transmitted sequence candidates;

a transmitted symbol candidate selector for selecting and outputting symbol candidates for (M-L) converted signals based on said received signals;

25   a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, and said symbol candidates; and

        a restorer for restoring and outputting at least one of said

30   transmitted sequence, the likelihood for said transmitted sequence, and the likelihood for bits transmitted by said transmitted sequence, based on the output from said transmitted sequence estimator and said priorities.

       14.   A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator includes likelihood calculator groups and signal selectors in P stages (P is an integer of 1 or greater);

5   a likelihood calculator group in a pth (p is an integer ranging from 1 to P) stage comprising Kp (Kp is an integer of 1 or greater) likelihood calculators;

        each of said likelihood calculators calculating a likelihood in the pth stage and generating said transmitted symbol candidates based on the

10   converted signal, said R matrix, Lp-1 (Lp-1 is an integer of 1 or greater) error signals output from a signal selector in a (p-1)th stage, and the transmitted symbol candidates; and

        a signal selector in the pth stage outputting Lp (Lp is an integer of 1 or greater) maximum likelihoods and Lp transmitted symbol candidates

15   which give the likelihoods, based on Kp likelihoods output from the likelihood calculator group in the pth stage and said transmitted symbol candidates.

15.   A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator includes likelihood calculator groups and signal selectors in P stages (P is an integer of 1 or greater);

a likelihood calculator group in a pth (p is an integer ranging from 1 to P) stage comprising K_p (K_p is an integer of 1 or greater) likelihood calculators;

each of said likelihood calculators calculating a likelihood in the pth stage and generating said transmitted symbol candidates based on the converted signal, said R matrix, K_p-1 (K_p-1 is an integer of 1 or greater) error signals output from a signal selector in a (p-1)th stage, and the transmitted symbol candidates; and

a signal selector in the pth stage outputting K_p+1 maximum likelihoods and K_p+1 transmitted symbol candidates which give the likelihoods, based on K_p likelihoods output from the likelihood calculator group in the pth stage and said transmitted symbol candidates.

16.   A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator comprises likelihood calculator groups in M stages (M is an integer of 2 or greater) and signal selector groups in the M stages.

17.   A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator comprises likelihood calculator groups in N stages (N is an integer of 2 or greater) and signal selector groups in the M stages.

18.　A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects and outputs a most likely transmitted sequence.

5

19.　A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects a most likely transmitted sequence and outputs a likelihood for said

5　sequence.

20.　A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects a most likely transmitted sequence and outputs a likelihood for a bit

5　sequence transmitted by said sequence.

21.　A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator includes a likelihood calculator for generating a converted signal replica using elements of said R matrix and calculating the likelihood using a physical quantity

5　measured from said converted signal replica and said received signals.

22.　A wireless communication system according to claim 21, wherein said likelihood calculator calculates the likelihood using a squared Euclidean

distance between said received signals and said converted signal replica.

23. A wireless communication system according to claim 21, wherein said likelihood calculator calculates the likelihood using a Euclidean distance converted by performing a given processing operation on a squared Euclidean distance between said received signals and said converted signal

5 replica.

24. A wireless communication system according to any one of claims 7, 10, 12, 13, wherein said transmitted symbol candidate selector employs a linear filter.

25. A wireless communication system according to any one of claims 7, 10, 12, 13, wherein said transmitted symbol candidate selector employs maximum likelihood estimation.

26. A wireless communication system according to any one of claims 8, 10, 11, 13, wherein said priority determiner employs received electric power of each of said transmitted sequences.

27. A wireless communication system according to any one of claims 8, 10, 11, 13, wherein said priority determiner employs a received electric power vs. noise electric power ratio of each of said transmitted sequences.

28. A wireless communication system according to any one of claims 8, 10, 11, 13, wherein said priority determiner employs a received electric

power vs. noise electric power ratio and an interference electric power ratio of each of said transmitted sequences.

5

29.   A wireless communication system according to any one of claims 9, 11, 12, and 13, wherein said transmitted sequence candidate selector employs a linear filter.

30.   A wireless communication system according to any one of claims 9, 11, 12, and 13, wherein said transmitted sequence candidate selector employs maximum likelihood estimation.

31.   A wireless communication system according to any one of claims 8, 10, 11, 13, wherein data sequences transmitted from M transmission antennas are modulated respectively by independent modulating processes, and said modulating processes have respective different numbers of signal

5   points, and said priority determiner determines said priorities based on said modulating processes for the respective transmission antennas.

32.   A wireless communication system according to claim 31, wherein a priority is given to an antenna which has sequences of a lower modulation multi-valued number among said transmission antennas.

33.   A wireless communication system according to any one of claims 14 through 20, wherein data sequences transmitted from M transmission antennas are modulated respectively by independent modulating processes, and said modulating processes have respective different numbers of signal

5   points, and said signal selector determines the number of error signals and transmitted symbol candidates which are output depending on the modulating process for the transmission antenna to be processed by a likelihood calculator in a next stage.

34.   A wireless communication system according to any one of claims 6 through 13, wherein said transmitted sequence estimator includes a likelihood calculator for calculating the likelihood using the difference between a squared Euclidean distance between a converted signal replica at

5   a bit 0 and the received signals and a squared Euclidean distance between a converted signal replica at a bit 1 and the received signals.

35.   A wireless communication system according to claim 34, wherein said transmitted sequence estimator includes an accumulator for accumulating a first squared Euclidean distance between a converted signal replica at a bit 0 and the received signals and a second squared Euclidean

5   distance between a converted signal replica at a bit 1 and the received signals, and outputting a provisional squared Euclidean distance based on the accumulated squared Euclidean distances; and

wherein said likelihood calculator calculates the likelihood using said provisional squared Euclidean distance if either one of said first and

10   second squared Euclidean distances is not output.

36.   A wireless communication system according to claim 34 or 35, wherein said squared Euclidean distance is replaced with a Euclidean distance which is converted by performing a given functional operation on

said squared Euclidean distance.

5

37.   A wireless communication system according to any one of claims 8, 10, 11, 13, wherein data sequences transmitted from M transmission antennas are modulated respectively by independent modulating processes, and said modulating processes have respective independent coding ratios,

5   and said priority determiner determines said priorities based on the coding ratios for the respective transmission antennas.

38.   A wireless communication system according to any one of claims 6 through 13, wherein said channel coefficient estimator estimates, in the transmitting apparatus having the M (M is an integer of 2 or greater) transmission antennas, the channel coefficients using pilot symbols

5   periodically transmitted according to a symbol pattern inherent in each of the transmission antennas and known to the receiving apparatus.

39.   A wireless communication system according to any one of claims 6 through 13, wherein said transmitting apparatus spreads in advance and then transmits the transmitted signals, and said Q^H processor multiplies the received signal vector having said received signals after being despread as

5   elements by the complex conjugate transposed matrix of said Q matrix and outputs the product as the converted signal.

40.   A wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, with a receiving apparatus having N

(N is an integer of 2 or greater), said receiving apparatus comprising:

5   means for using a Euclidean distance converted by performing a given processing operation on a squared Euclidean distance.

41.   A wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, with a receiving apparatus having N (N is an integer of 2 or greater), said receiving apparatus comprising:

5   .   an accumulator for accumulating a first squared Euclidean distance at a bit 0 and a second squared Euclidean distance at a bit 1, and outputting a provisional squared Euclidean distance based on the accumulated squared Euclidean distances; and

         means for calculating a likelihood using said provisional squared

10   Euclidean distance if either one of said first and second squared Euclidean distances is not output.

42..   A wireless communication system according to claim 41, wherein said squared Euclidean distance is replaced with a Euclidean distance which is converted by performing a given functional operation on said squared Euclidean distance.

5

43.   A receiving apparatus having N (N is an integer of 2 or greater) reception antennas in a wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, said receiving apparatus

5   comprising:

means for performing nulling representative of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission antennas; and

means for demodulating said transmitted signals based on the

10   nulled signals.

44.   A receiving apparatus having N (N is an integer of 2 or greater) reception antennas in a wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, said receiving apparatus

5   comprising:

means for performing nulling representative of orthogonalization of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission antennas; and

10   means for calculating and outputting a likelihood for said transmitted signals based on the nulled signals.

45.   A receiving apparatus having N (N is an integer of 2 or greater) reception antennas in a wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, said receiving apparatus

5   comprising:

means for performing nulling representative of orthogonalization of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission

antennas; and

10   means for outputting a likelihood for bits of said transmitted

signals based on the nulled signals.

46.   A receiving apparatus according to any one of claims 43 through
45, wherein said means for performing nulling uses a complex conjugate
transposed matrix of a Q matrix produced by QR-decomposing the channel
matrix as nulling.

5

47.   A receiving apparatus according to any one of claims 43 through
45, wherein said transmitted signals are demodulated in a descending order
from a transmitted sequence transmitted from an Mth transmitted antenna to
a transmitted sequence transmitted from a first transmitted antenna, based

5   on the nulled signals.

48.   A receiving apparatus according to any one of claims 43 through
47, comprising:

a channel coefficient estimator for estimating and outputting said
channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the
channel matrix of said channel coefficients and outputting a Q matrix and an
R matrix;

a Q^H processor for multiplying a received signal vector having

10   said received signals as elements by a complex conjugate transposed matrix
of said Q matrix and outputting the product as a converted signal; and

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said

15 converted signal and said R matrix.

49. A receiving apparatus according to any one of claims 43 through 47, comprising:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5 transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the channel matrix of said channel coefficients and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having

10 said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted symbol candidate selector for selecting and outputting a symbol candidate for said converted signal based on said received signals; and

15 a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said symbol candidate, and said R matrix.

50. A receiving apparatus according to any one of claims 43 through 47, comprising:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the

10   channel coefficients estimated by said channel coefficient estimator and the priorities determined by said priority determiner, and outputting a modified channel matrix;

a QR decomposer for performing QR decomposition on said modified channel matrix and outputting a Q matrix and an R matrix;

15   a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a

20   likelihood for bits transmitted by said transmitted sequence, based on said converted signal and said R matrix; and

a restorer for restoring and outputting at least one of said transmitted sequence, the likelihood for said transmitted sequence, and the likelihood for bits transmitted by said transmitted sequence, based on the

25   output from said transmitted sequence estimator and said priorities.

51.   A receiving apparatus according to any one of claims 43 through 47, comprising:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5 transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the channel matrix of said channel coefficients and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having

10 said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted signals based on said received signals and outputting the determined

15 candidate sequences as transmitted sequence candidates; and

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, and said transmitted sequence candidates.

20

52. A receiving apparatus according to any one of claims 43 through 47, comprising:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5 transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the

10 channel coefficients estimated by said channel coefficient estimator and the

priorities determined by said priority determiner, and outputting a modified

channel matrix;

a QR decomposer for performing QR decomposition on said

modified channel matrix and outputting a Q matrix and an R matrix;

15 a Q^H processor for multiplying a received signal vector having

said received signals as elements by a complex conjugate transposed matrix

of said Q matrix and outputting the product as a converted signal;

a transmitted symbol candidate selector for selecting a symbol

candidate for a demodulated sequence based on said received signals, and

20 outputting a transmitted symbol candidate;

a transmitted sequence estimator for outputting at least one of a

transmitted sequence, a likelihood for said transmitted sequence, and a

likelihood for bits transmitted by said transmitted sequence, based on said

converted signal, said R matrix, and said transmitted symbol candidate; and

25 a restorer for restoring and outputting at least one of said

transmitted sequence, the likelihood for said transmitted sequence, and the

likelihood for bits transmitted by said transmitted sequence, based on the

output from said transmitted sequence estimator and said priorities.

53. A receiving apparatus according to any one of claims 43 through

47, comprising:

a channel coefficient estimator for estimating and outputting said

channel coefficients between said between said reception antennas and said

5 transmission antennas based on said received signals;

100

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the

10 channel coefficients estimated by said channel coefficient estimator and the priorities determined by said priority determiner, and outputting a modified channel matrix;

a QR decomposer for performing QR decomposition on said modified channel matrix and outputting a Q matrix and an R matrix;

15 a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted

20 signals based on said received signals and outputting the determined candidate sequences as transmitted sequence candidates;

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said

25 converted signal, said R matrix, and said transmitted sequence candidates; and

a restorer for restoring and outputting at least one of said transmitted sequence, the likelihood for said transmitted sequence, and the likelihood for bits transmitted by said transmitted sequence, based on the

30 output from said transmitted sequence estimator and said priorities.

54.   A receiving apparatus according to any one of claims 43 through 47, comprising:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the channel matrix of said channel coefficients and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having

10   said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted signals based on said received signals and outputting the determined

15   candidate sequences as transmitted sequence candidates;

a transmitted symbol candidate selector for selecting and outputting symbol candidates for (M-L) demodulated signals based on said received signals; and

a transmitted sequence estimator for outputting at least one of a

20   transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, said transmitted sequence candidates, and said symbol candidates.

55.   A receiving apparatus according to any one of claims 43 through 47, comprising:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the channel coefficients estimated by said channel coefficient estimator and the priorities determined by said priority determiner, and outputting a modified channel matrix;

a QR decomposer for performing QR decomposition on said modified channel matrix and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted signals based on said received signals and outputting the determined candidate sequences as transmitted sequence candidates;

a transmitted symbol candidate selector for selecting and outputting symbol candidates for (M-L) converted signals based on said received signals;

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, and said symbol candidates; and

103

a restorer for restoring and outputting at least one of said

30 transmitted sequence, the likelihood for said transmitted sequence, and the

likelihood for bits transmitted by said transmitted sequence, based on the

output from said transmitted sequence estimator and said priorities.

56. A receiving apparatus according to any one of claims 48 through

55, wherein said transmitted sequence estimator includes likelihood

calculator groups and signal selectors in P stages (P is an integer of 1 or

greater);

5 a likelihood calculator group in a pth (p is an integer ranging from

1 to P) stage comprising Kp (Kp is an integer of 1 or greater) likelihood

calculators;

each of said likelihood calculators calculating a likelihood in the

pth stage and generating said transmitted symbol candidates based on the

10 converted signal, said R matrix, Lp-1 (Lp-1 is an integer of 1 or greater) error

signals output from a signal selector in a (p-1)th stage, and the transmitted

symbol candidates; and

a signal selector in the pth stage outputting Lp (Lp is an integer of

1 or greater) maximum likelihoods and Lp transmitted symbol candidates

15 which give the likelihoods, based on Kp likelihoods output from the likelihood

calculator group in the pth stage and said transmitted symbol candidates.

57. A receiving apparatus according to any one of claims 48 through

55, wherein said transmitted sequence estimator includes likelihood

calculator groups and signal selectors in P stages (P is an integer of 1 or

greater);

a likelihood calculator group in a pth (p is an integer ranging from 1 to P) stage comprising Kp (Kp is an integer of 1 or greater) likelihood calculators;

each of said likelihood calculators calculating a likelihood in the pth stage and generating said transmitted symbol candidates based on the converted signal, said R matrix, Kp-1 (Kp-1 is an integer of 1 or greater) error signals output from a signal selector in a (p-1)th stage, and the transmitted symbol candidates; and

a signal selector in the pth stage outputting Kp+1 maximum likelihoods and Kp+1 transmitted symbol candidates which give the likelihoods, based on Kp likelihoods output from the likelihood calculator group in the pth stage and said transmitted symbol candidates.

58.   A receiving apparatus according to any one of claims 48 through 55, wherein said transmitted sequence estimator comprises likelihood calculator groups in M stages (M is an integer of 2 or greater) and signal selector groups in the M stages.

59.   A receiving apparatus according to any one of claims 48 through 55, wherein said transmitted sequence estimator comprises likelihood calculator groups in N stages (N is an integer of 2 or greater) and signal selector groups in the M stages.

60.   A receiving apparatus according to any one of claims 48 through 55, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects and outputs

a most likely transmitted sequence.

5

61. A receiving apparatus according to any one of claims 48 through 55, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects a most likely transmitted sequence and outputs a likelihood for said sequence.

5

62. A receiving apparatus according to any one of claims 48 through 55, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects a most likely transmitted sequence and outputs a likelihood for a bit sequence

5 transmitted by said sequence.

63. A receiving apparatus according to any one of claims 48 through 55, wherein said transmitted sequence estimator includes a likelihood calculator for generating a converted signal replica using elements of said R matrix and calculating the likelihood using a physical quantity measured from

5 said converted signal replica and said received signals.

64. A receiving apparatus according to claim 63, wherein said likelihood calculator calculates the likelihood using a squared Euclidean distance between said received signals and said converted signal replica.

65. A receiving apparatus according to claim 63, wherein said likelihood calculator calculates the likelihood using a Euclidean distance converted by performing a given processing operation on a squared

Euclidean distance between said received signals and said converted signal

5   replica.

66.   A receiving apparatus according to any one of claims 49, 51, 54, 55, wherein said transmitted symbol candidate selector employs a linear filter.

67.   A receiving apparatus according to any one of claims 49, 51, 54, 55, wherein said transmitted symbol candidate selector employs maximum likelihood estimation.

68.   A receiving apparatus according to any one of claims 50, 52, 53, 55, wherein said priority determiner employs received electric power of each of said transmitted sequences.

69.   A receiving apparatus according to any one of claims 50, 52, 53, 55, wherein said priority determiner employs a received electric power vs. noise electric power ratio of each of said transmitted sequences.

70.   A receiving apparatus according to any one of claims 50, 52, 53, 55, wherein said priority determiner employs a received electric power vs. noise electric power ratio and an interference electric power ratio of each of said transmitted sequences.

5

71.   A receiving apparatus according to any one of claims 51, 53, 54, 55, wherein said transmitted sequence candidate selector employs a linear

filter.

72. A receiving apparatus according to any one of claims 51, 53, 54, 55, wherein said transmitted sequence candidate selector employs maximum likelihood estimation.

73. A receiving apparatus according to any one of claims 50, 52, 53, 54, wherein data sequences transmitted from M transmission antennas are modulated respectively by independent modulating processes, and said modulating processes have respective different numbers of signal points,

5 and said priority determiner determines said priorities based on said modulating processes for the respective transmission antennas.

74. A receiving apparatus according to claim 73, wherein a priority is given to an antenna which has sequences of a lower modulation multi-valued number among said transmission antennas.

75. A receiving apparatus according to any one of claims 56 through 62, wherein data sequences transmitted from M transmission antennas are modulated respectively by independent modulating processes, and said modulating processes have respective different numbers of signal points,

5 and said signal selector determines the number of error signals and transmitted symbol candidates which are output depending on the modulating process for the transmission antenna to be processed by a likelihood calculator in a next stage.

76. A receiving apparatus according to any one of claims 48 through 55, wherein said transmitted sequence estimator includes a likelihood calculator for calculating the likelihood using the difference between a squared Euclidean distance between a converted signal replica at a bit 0 and the received signals and a squared Euclidean distance between a converted signal replica at a bit 1 and the received signals.

77. A receiving apparatus according to claim 76, wherein said transmitted sequence estimator includes an accumulator for accumulating a first squared Euclidean distance between a converted signal replica at a bit 0 and the received signals and a second squared Euclidean distance between a converted signal replica at a bit 1 and the received signals, and outputting a provisional squared Euclidean distance based on the accumulated squared Euclidean distances; and

wherein said likelihood calculator calculates the likelihood using said provisional squared Euclidean distance if either one of said first and second squared Euclidean distances is not output.

78. A receiving apparatus according to claim 76 or 77, wherein said squared Euclidean distance is replaced with a Euclidean distance which is converted by performing a given functional operation on said squared Euclidean distance.

79. A receiving apparatus according to any one of claims 46, 48, 49, 51, wherein data sequences transmitted from M transmission antennas are modulated respectively by independent modulating processes, and said

modulating processes have respective independent coding ratios, and said

5   priority determiner determines said priorities based on the coding ratios for

the respective transmission antennas.

80.   A receiving apparatus according to any one of claims 48 through

55, wherein said channel coefficient estimator estimates, in the transmitting

apparatus having the M (M is an integer of 2 or greater) transmission

antennas, the channel coefficients using pilot symbols periodically

5   transmitted according to a symbol pattern inherent in each of the

transmission antennas and known to the receiving apparatus.

81.   A receiving apparatus according to any one of claims 48 through

55, wherein said transmitting apparatus spreads in advance and then

transmits the transmitted signals, and said Q^H processor multiplies the

received signal vector having said received signals after being despread as

5   elements by the complex conjugate transposed matrix of said Q matrix and

outputs the product as the converted signal.

82.   A receiving apparatus having N (N is an integer of 2 or greater)

reception antennas in a wireless communication system for receiving and

demodulating transmitted signals from a transmitting apparatus having M (M

is an integer of 2 or greater) transmission antennas, said receiving apparatus

5   comprising:

means for using a Euclidean distance converted by performing a

given processing operation on a squared Euclidean distance.

83.   A receiving apparatus having N (N is an integer of 2 or greater) reception antennas in a wireless communication system for receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, said receiving apparatus

5   comprising:

an accumulator for accumulating a first squared Euclidean distance at a bit 0 and a second squared Euclidean distance at a bit 1, and outputting a provisional squared Euclidean distance based on the accumulated squared Euclidean distances; and

10   means for calculating a likelihood using said provisional squared Euclidean distance if either one of said first and second squared Euclidean distances is not output.

84.   A recording apparatus according to claim 83, wherein said squared Euclidean distance is replaced with a Euclidean distance which is converted by performing a given functional operation on said squared Euclidean distance.

5

85.   A demodulating method of receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, in a receiving apparatus having N (N is an integer of 2 or greater) reception antennas, said demodulating method

5   comprising the steps of:

performing nulling representative of orthogonalization of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission

antennas; and

10   demodulating said transmitted signals based on the nulled

signals.

86.   A demodulating method of receiving and demodulating

transmitted signals from a transmitting apparatus having M (M is an integer

of 2 or greater) transmission antennas, in a receiving apparatus having N (N

is an integer of 2 or greater) reception antennas, said demodulating method

5   comprising the steps of:

performing nulling representative of orthogonalization of the

received signals, using a channel matrix having as elements channel

coefficients between said reception antennas and said transmission

antennas; and

10   calculating and outputting a likelihood for said transmitted signals

based on the nulled signals.

87.   A demodulating method of receiving and demodulating

transmitted signals from a transmitting apparatus having M (M is an integer

of 2 or greater) transmission antennas, in a receiving apparatus having N (N

is an integer of 2 or greater) reception antennas, said demodulating method

5   comprising the steps of:

performing nulling representative of orthogonalization of the

received signals, using a channel matrix having as elements channel

coefficients between said reception antennas and said transmission

antennas; and

10   outputting a likelihood for bits of said transmitted signals based

on the nulled signals.

88.   A demodulating method according to any one of claims 85 through 87, wherein said step of performing nulling uses a complex conjugate transposed matrix of a Q matrix produced by QR-decomposing the channel matrix as nulling.

5

89.   A demodulating method according to any one of claims 85 through 87, wherein said transmitted signals are demodulated in a descending order from a transmitted sequence transmitted from an Mth transmitted antenna to a transmitted sequence transmitted from a first transmitted antenna, based on the nulled signals.

5

90.   A demodulating method according to any one of claims 85 through 89, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said transmission antennas based on said received signals;

5

a QR decomposer for performing QR decomposition on the channel matrix of said channel coefficients and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal; and

10

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a

likelihood for bits transmitted by said transmitted sequence, based on said

15   converted signal and said R matrix.

91.   A demodulating method according to any one of claims 85

through 89, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said

channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the

channel matrix of said channel coefficients and outputting a Q matrix and an

R matrix;

a Q^H processor for multiplying a received signal vector having

10   said received signals as elements by a complex conjugate transposed matrix

of said Q matrix and outputting the product as a converted signal;

a transmitted symbol candidate selector for selecting and

outputting a symbol candidate for said converted signal based on said

received signals; and

15   a transmitted sequence estimator for outputting at least one of a

transmitted sequence, a likelihood for said transmitted sequence, and a

likelihood for bits transmitted by said transmitted sequence, based on said

converted signal, said symbol candidate, and said R matrix.

92.   A demodulating method according to any one of claims 85

through 89, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said

channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a priority determiner for determining priorities between

transmission sequences transmitted from said transmission antennas based

on said received signals;

a sorter for sorting said channel coefficients based on the

10   channel coefficients estimated by said channel coefficient estimator and the

priorities determined by said priority determiner, and outputting a modified

channel matrix;

a QR decomposer for performing QR decomposition on said

modified channel matrix and outputting a Q matrix and an R matrix;

15   a Q^H processor for multiplying a received signal vector having

said received signals as elements by a complex conjugate transposed matrix

of said Q matrix and outputting the product as a converted signal;

a transmitted sequence estimator for outputting at least one of a

transmitted sequence, a likelihood for said transmitted sequence, and a

20   likelihood for bits transmitted by said transmitted sequence, based on said

converted signal and said R matrix; and

a restorer for restoring and outputting at least one of said

transmitted sequence, the likelihood for said transmitted sequence, and the

likelihood for bits transmitted by said transmitted sequence, based on the

25   output from said transmitted sequence estimator and said priorities.

93.   A demodulating method according to any one of claims 85

through 89, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said

channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the channel matrix of said channel coefficients and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having

10   said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted signals based on said received signals and outputting the determined

15   candidate sequences as transmitted sequence candidates; and

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, and said transmitted sequence candidates.

20

94.   A demodulating method according to any one of claims 85 through 89, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the

10   channel coefficients estimated by said channel coefficient estimator and the

116

priorities determined by said priority determiner, and outputting a modified channel matrix;

a QR decomposer for performing QR decomposition on said modified channel matrix and outputting a Q matrix and an R matrix;

15 a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted symbol candidate selector for selecting a symbol candidate for a demodulated sequence based on said received signals, and 20 outputting a transmitted symbol candidate;

a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, and said transmitted symbol candidate; and

25 a restorer for restoring and outputting at least one of said transmitted sequence, the likelihood for said transmitted sequence, and the likelihood for bits transmitted by said transmitted sequence, based on the output from said transmitted sequence estimator and said priorities.

95. A demodulating method according to any one of claims 85 through 89, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said 5 transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based

on said received signals;

a sorter for sorting said channel coefficients based on the
channel coefficients estimated by said channel coefficient estimator and the
priorities determined by said priority determiner, and outputting a modified
channel matrix;

a QR decomposer for performing QR decomposition on said
modified channel matrix and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having
said received signals as elements by a complex conjugate transposed matrix
of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining
candidate sequences for L (L is an integer ranging from 1 to M) converted
signals based on said received signals and outputting the determined
candidate sequences as transmitted sequence candidates;

a transmitted sequence estimator for outputting at least one of a
transmitted sequence, a likelihood for said transmitted sequence, and a
likelihood for bits transmitted by said transmitted sequence, based on said
converted signal, said R matrix, and said transmitted sequence candidates;
and

a restorer for restoring and outputting at least one of said
transmitted sequence, the likelihood for said transmitted sequence, and the
likelihood for bits transmitted by said transmitted sequence, based on the
output from said transmitted sequence estimator and said priorities.

96.   A demodulating method according to any one of claims 85
through 89, wherein said receiving apparatus comprises:

118

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5 transmission antennas based on said received signals;

a QR decomposer for performing QR decomposition on the channel matrix of said channel coefficients and outputting a Q matrix and an R matrix;

a Q^H processor for multiplying a received signal vector having

10 said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted signals based on said received signals and outputting the determined

15 candidate sequences as transmitted sequence candidates;

a transmitted symbol candidate selector for selecting and outputting symbol candidates for (M-L) demodulated signals based on said received signals; and

a transmitted sequence estimator for outputting at least one of a

20 transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, said transmitted sequence candidates, and said symbol candidates.

97.   A demodulating method according to any one of claims 85 through 89, wherein said receiving apparatus comprises:

a channel coefficient estimator for estimating and outputting said channel coefficients between said between said reception antennas and said

5   transmission antennas based on said received signals;

a priority determiner for determining priorities between transmission sequences transmitted from said transmission antennas based on said received signals;

a sorter for sorting said channel coefficients based on the

10   channel coefficients estimated by said channel coefficient estimator and the priorities determined by said priority determiner, and outputting a modified channel matrix;

a QR decomposer for performing QR decomposition on said modified channel matrix and outputting a Q matrix and an R matrix;

15   a Q^H processor for multiplying a received signal vector having said received signals as elements by a complex conjugate transposed matrix of said Q matrix and outputting the product as a converted signal;

a transmitted sequence candidate selector for determining candidate sequences for L (L is an integer ranging from 1 to M) converted

20   signals based on said received signals and outputting the determined candidate sequences as transmitted sequence candidates;

a transmitted symbol candidate selector for selecting and outputting symbol candidates for (M-L) converted signals based on said received signals;

25   a transmitted sequence estimator for outputting at least one of a transmitted sequence, a likelihood for said transmitted sequence, and a likelihood for bits transmitted by said transmitted sequence, based on said converted signal, said R matrix, and said symbol candidates; and

a restorer for restoring and outputting at least one of said

30   transmitted sequence, the likelihood for said transmitted sequence, and the

120

likelihood for bits transmitted by said transmitted sequence, based on the output from said transmitted sequence estimator and said priorities.

98. A demodulating method according to any one of claims 90 through 97, wherein said transmitted sequence estimator includes likelihood calculator groups and signal selectors in P stages (P is an integer of 1 or greater);

5   a likelihood calculator group in a pth (p is an integer ranging from 1 to P) stage comprising Kp (Kp is an integer of 1 or greater) likelihood calculators;

each of said likelihood calculators calculating a likelihood in the pth stage and generating said transmitted symbol candidates based on the

10   converted signal, said R matrix, Lp-1 (Lp-1 is an integer of 1 or greater) error signals output from a signal selector in a (p-1)th stage, and the transmitted symbol candidates; and

a signal selector in the pth stage outputting Lp (Lp is an integer of 1 or greater) maximum likelihoods and Lp transmitted symbol candidates

15   which give the likelihoods, based on Kp likelihoods output from the likelihood calculator group in the pth stage and said transmitted symbol candidates.

99. A demodulating method according to any one of claims 90 through 97, wherein said transmitted sequence estimator includes likelihood calculator groups and signal selectors in P stages (P is an integer of 1 or greater);

5   a likelihood calculator group in a pth (p is an integer ranging from 1 to P) stage comprising Kp (Kp is an integer of 1 or greater) likelihood

121

calculators;

each of said likelihood calculators calculating a likelihood in the pth stage and generating said transmitted symbol candidates based on the converted signal, said R matrix, Kp-1 (Kp-1 is an integer of 1 or greater) error signals output from a signal selector in a (p-1)th stage, and the transmitted symbol candidates; and

a signal selector in the pth stage outputting Kp+1 maximum likelihoods and Kp+1 transmitted symbol candidates which give the likelihoods, based on Kp likelihoods output from the likelihood calculator group in the pth stage and said transmitted symbol candidates.

100. A demodulating method according to any one of claims 90 through 97, wherein said transmitted sequence estimator comprises likelihood calculator groups in M stages (M is an integer of 2 or greater) and signal selector groups in the M stages.

101. A demodulating method according to any one of claims 90 through 97, wherein said transmitted sequence estimator comprises likelihood calculator groups in M stages (M is an integer of 2 or greater) and signal selector groups in the M stages.

102. A demodulating method according to any one of claims 90 through 97, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects and outputs a most likely transmitted sequence.

103. A demodulating method according to any one of claims 90 through 97, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects a most likely transmitted sequence and outputs a likelihood for said

5   sequence.

104. A demodulating method according to any one of claims 90 through 97, wherein said transmitted sequence estimator includes signal selectors in a plurality of stages, and a signal selector in a final stage selects a most likely transmitted sequence and outputs a likelihood for a bit

5   sequence transmitted by said sequence.

105. A demodulating method according to any one of claims 90 through 97, wherein said transmitted sequence estimator includes a likelihood calculator for generating a converted signal replica using elements of said R matrix and calculating the likelihood using a physical quantity

5   measured from said converted signal replica and said received signals.

106. A demodulating method according to claim 105, wherein said likelihood calculator calculates the likelihood using a squared Euclidean distance between said received signals and said converted signal replica.

107. A demodulating method according to claim 105, wherein said likelihood calculator calculates the likelihood using a Euclidean distance converted by performing a given processing operation on a squared Euclidean distance between said received signals and said converted signal

5   replica.

108. A demodulating method according to any one of claims 91, 94, 96, 97, wherein said transmitted symbol candidate selector employs a linear filter.

109. A demodulating method according to any one of claims 91, 94, 96, 97, wherein said transmitted symbol candidate selector employs maximum likelihood estimation.

110. A demodulating method according to any one of claims 92, 94, 95, 97, wherein said priority determiner employs received electric power of each of said transmitted sequences.

111. A demodulating method according to any one of claims 92, 94, 95, 97, wherein said priority determiner employs a received electric power vs. noise electric power ratio of each of said transmitted sequences.

112. A demodulating method according to any one of claims 92, 94, 95, 97, wherein said priority determiner employs a received electric power vs. noise electric power ratio and an interference electric power ratio of each of said transmitted sequences.

5

113. A demodulating method according to any one of claims 93, 95, 96, 97, wherein said transmitted sequence candidate selector employs a linear filter.

114. A demodulating method according to any one of claims 93, 95, 96, 97, wherein said transmitted sequence candidate selector employs maximum likelihood estimation.

115. A demodulating method according to any one of claims 92, 94, 95, 97, wherein data sequences transmitted from M transmission antennas are modulated respectively by independent modulating processes, and said modulating processes have respective different numbers of signal points,

5   and said priority determiner determines said priorities based on said modulating processes for the respective transmission antennas.

116. A demodulating method according to claim 115, wherein a priority is given to an antenna which has sequences of a lower modulation multi-valued number among said transmission antennas.

117. A demodulating method according to any one of claims 98 through 104, wherein data sequences transmitted from M transmission antennas are modulated respectively by independent modulating processes, and said modulating processes have respective different numbers of signal

5   points, and said signal selector determines the number of error signals and transmitted symbol candidates which are output depending on the modulating process for the transmission antenna to be processed by a likelihood calculator in a next stage.

118. A demodulating method according to any one of claims 90

through 97, wherein said transmitted sequence estimator includes a

likelihood calculator for calculating the likelihood using the difference

between a squared Euclidean distance between a converted signal replica at

5   a bit 0 and the received signals and a squared Euclidean distance between a

converted signal replica at a bit 1 and the received signals.

119. A demodulating method according to claim 118, wherein said

transmitted sequence estimator includes an accumulator for accumulating a

first squared Euclidean distance between a converted signal replica at a bit 0

and the received signals and a second squared Euclidean distance between

5   a converted signal replica at a bit 1 and the received signals, and outputting

a provisional squared Euclidean distance based on the accumulated squared

Euclidean distances; and

120. A demodulating method according to claim 118 or 119, wherein

said squared Euclidean distance is replaced with a Euclidean distance which

is converted by performing a given functional operation on said squared

Euclidean distance.

5

121. A demodulating method according to any one of claims 92, 94,

95, 97, wherein data sequences transmitted from M transmission antennas

are modulated respectively by independent modulating processes, and said

modulating processes have respective independent coding ratios, and said

5   priority determiner determines said priorities based on the coding ratios for

the respective transmission antennas.

122. A demodulating method according to any one of claims 90 through 97, wherein said channel coefficient estimator estimates, in the transmitting apparatus having the M (M is an integer of 2 or greater) transmission antennas, the channel coefficients using pilot symbols

5   periodically transmitted according to a symbol pattern inherent in each of the transmission antennas and known to the receiving apparatus.

123. A demodulating method according to any one of claims 90 through 97, wherein said transmitting apparatus spreads in advance and then transmits the transmitted signals, and said Q^H processor multiplies the received signal vector having said received signals after being despread as

5   elements by the complex conjugate transposed matrix of said Q matrix and outputs the product as the converted signal.

124. A demodulating method of receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, in a receiving apparatus having N (N is an integer of 2 or greater) reception antennas, said demodulating method

5   comprising the step of:

using a Euclidean distance converted by performing a given processing operation on a squared Euclidean distance.

125. A demodulating method of receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, in a receiving apparatus having N (N is an integer of 2 or greater) reception antennas, said demodulating method

5   comprising the steps of:

accumulating a first squared Euclidean distance at a bit 0 and a

second squared Euclidean distance at a bit 1, and outputting a provisional

squared Euclidean distance based on the accumulated squared Euclidean

distances; and

10   calculating a likelihood using said provisional squared Euclidean

distance if either one of said first and second squared Euclidean distances is

not output.

126. A demodulating method according to claim 125, wherein said

squared Euclidean distance is replaced with a Euclidean distance which is

converted by performing a given functional operation on said squared

Euclidean distance.

5

127. A program for a demodulating method of receiving and

demodulating transmitted signals from a transmitting apparatus having M (M

is an integer of 2 or greater) transmission antennas, in a receiving apparatus

having N (N is an integer of 2 or greater) reception antennas, said program

5   enabling a computer to perform:

a process of performing nulling representative of

orthogonalization of the received signals, using a channel matrix having as

elements channel coefficients between said reception antennas and said

transmission antennas; and

10   a process of demodulating said transmitted signals based on the

nulled signals.

128. A program for a demodulating method of receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, in a receiving apparatus having N (N is an integer of 2 or greater) reception antennas, said program

5   enabling a computer to perform:

a process of performing nulling representative of orthogonalization of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission antennas; and

10   a process of calculating and outputting a likelihood for said transmitted signals based on the nulled signals.

129. A program for a demodulating method of receiving and demodulating transmitted signals from a transmitting apparatus having M (M is an integer of 2 or greater) transmission antennas, in a receiving apparatus having N (N is an integer of 2 or greater) reception antennas, said program

5   enabling a computer to perform:

a process of performing nulling representative of orthogonalization of the received signals, using a channel matrix having as elements channel coefficients between said reception antennas and said transmission antennas; and

10   a process of outputting a likelihood for bits of said transmitted signals based on the nulled signals.